


The **NOMAD POWER PRO TRUCK** is a lithium-based power pack that combines three separate functions:
























- A booster for 12/24 V vehicles (*motorbikes, quad bikes, cars, SUVs and HGVs <19 T*).
- An autonomous power supply for small electronic devices.
- An emergency lamp

LITHIUM BATTERY BOOSTER

Its **lithium** battery gives it an exceptional power-to-size ratio (*with a starting current of 600 A*). It starts vehicles equipped with a discharged 12 V battery (*liquid, gel, AGM, Start&Stop*) in just a few seconds.

It also helps to start vehicles fitted with 24 V batteries.

( do not start Lithium LiFePO₄ batteries with this booster, battery voltages not compatible).

START	12 V / 24 V	PETROL & DIESEL
		
		
		
		
		
		
		
		

SAFETY START

The smart jump lead cable protects both the battery and the vehicle's on-board electronics:

- Anti-spark technology
- Short circuit protection
- Polarity reversal protection
- Excessive start-up current protection
- Booster temperature rise protection

MOBILE ENERGY SOURCE

Its extensive storage capacity (5.3 Ah) brings peace of mind ensuring consistently connected electronic equipment (*phones, tablets and computers*).

Equipped with:

- **2 x 5 V USB ports** (1 A / 2.1 A) for charging smartphones, tablets and GPS machines, etc.
- **A cigarette-lighter output port 12 V - 10 A**, ideal for supplying a 12 V electrical appliance while camping (*cool boxes and fans, etc.*).

HIGH BRIGHTNESS EMERGENCY LAMP

An emergency lamp offering three lighting modes: normal, strobe and SOS.

LCD DISPLAY

The NOMAD POWER PRO TRUCK is equipped with an LCD screen which displays:

- the battery's power level
- the internal battery's charge %
- which inputs and outputs are being used



LCD screen










Supplied with accessories:



12 V charger



Charging cable
Micro USB Type C

STARTING					EQUIPMENT			INPUT / OUTPUT				POWER BANK		LED	DIMENSIONS						
Lithium		I			SMART CABLE			CABLES 			INPUT	OUTPUT									
Capacity per cell	Full charge	Start	Cranking CC	Peak Battery				J3s	USB-C	MICRO USB Type B		Lightning	5V - 2A	9V - 2A					12V - 1.5A	5V - 1A	12V
5.3 Ah 137 Wh	10 h	600 A	1500 A	2000 A	12 V : 14000 J	—	✓	—	—	✓	—	5V - 2A 9V - 2A 12V - 1.5A	2	5V - 1A 5V - 2.1A	10 A	—	✓	✓	3 modes : Light SOS SPOT	24.8 x 24.8 x 9.6	2.4